

## LD-30FTA-1AD Analog input board

Type	Applicable model	Note
LD-30FTA-1AD	LD-30FTA	Sensor input of Tension controller

Usage : To detect reel diameter by touch lever potentiometer input or the ultrasonic input, the analog input board (option board) is installed in LD-30FTA.

### Installation method :

- 1) Turn off the power supply of LD-30FTA when you remove or install the analog input board.
- 2) Open the panel of LD-30FTA and remove the upper printed board (Z581C07701) inside and the flat cable.
- 3) Please insert spacer (accessory) to ensure LD-30FTA-1AD in securely fitted as shown in Figure 2.

Warning : Removal of the analog input board during operation may result in serious malfunction of the product.

- 4) Please install LD-30FTA-1AD in LD-30FTA I/O board (Z331A53104) with connector J1/J2 as shown in Figure 1.
- 5) Please return the upper printed board (Z581C07701) and the flat cable to former state.

\*Please see the product manual of LD-30FTA about other use.

November 2005  
JZ990D41501A

MADE IN JAPAN  
Mitsubishi Electric Corporation

